



Switch Between Four HDMI Sources To Two Displays



EXT-HDMI-442

Access up to Four Sources From One or Two Displays

Gefen's 4x2 HDMI Switcher routes high definition video in multiple resolutions of up to 1080p plus multichannel digital audio. The inputs accommodate the simultaneous connection of up to four high definition video sources, such as satellite systems and HD DVD players. Two outputs send the high definition audio/video signals to up to two high definition displays. A digital audio output port is available if you need to direct the audio to an audio receiver. Switching is done via the IR remote that is provided with the unit.

Features:

- Switch easily between any four HDMI sources
- Outputs are mirrored to two HDMI Displays
- Additional digital coax audio output extracted from HDMI input for easy connection to multi-channel audio receivers
- Extends the range of HDMI compliant device by equalizing and reclocking the HDMI signal
- Maintains high resolution video - beautiful, sharp HDTV resolutions up to 1080p, 2k, and computer resolutions up to 1920 x 1200 are easily achieved
- Discrete IR remote (included)
- Serial RS-232 remote port
- HDMI compliant
- HDCP compliant

How It Works

You simply connect all your sources to the Switcher's inputs. Then connect up to two displays on the output ports. Once the sources, the Switcher and the display(s) are powered and connected, you simply select which source you want to view using the included IR remote.

Specifications:

- Gefen's Video Amplifier Bandwidth: 165 MHz
- Input Video Signal: 1.2 Volts p-p
- Input DDC Signal: 5 Volts p-p (TTL)
- Single Link Range: 1080p/1920 x 1200
- HDMI Connector: Type A 19 Pin Female
- Digital Audio Output: S/PDIF
- Remote Control Port: female RS232, mini-stereo
- Power Supply: 5V DC
- Power Consumption: 20 Watts (max)
- Dimensions: 11"W x 1.25"H x 4.25"D
- Shipping Weight: 6 lbs.